



KUHNKE

The Timer & Counter Company
H. Kuhnke Ltd
 Unit 6 Focus 303
 Focus Way, Walworth Business Park
 Andover, Hampshire
 SP10 5NY, United Kingdom

Telephone: +44 (0)1264 364194

Facsimile: +44 (0)1264 365991

Email: sales@kuhnke.co.uk

www.thetimerandcountercompany.com

Pneumatic Adding Preset Counters - 50.695 / 50.700

- 3 digit two line display
- Manual & pneumatic reset
- Convenient button setting
- M5 ports and 4mm push-in fittings
- Maintenance free operation
- Light & durable

Display	3 digit
Digit Height	4mm
Operating Pressure	2-8 bar
Air Quality	Oil free and dry, 5 micron filtered
Mechanical Life	30 x 10 ⁶
Protection Class	IP40
Operating Temperature	0...+60°C
Connection	M5 female threaded ports / 4mm push-in
Mounting Position	Panel mounting (cut out 52mm x 52mm)
Count Input	Adding
Pulse Length Min	8ms minimum
Count Frequency max	20Hz
Pulse duty factor	The non pulse period must be long enough to allow pressure to drop to approx. 0.15 bar for a minimum of 12ms

Reset	Manual with button or pneumatic reset minimum pulse length 180ms.
Reset Frequency	1 reset per 2 seconds
Output Signal Duration	From when counter has reached preset until reset. Please Note: minimum time period between last count pulse and pneumatic reset is 50ms

PART NUMBERS	
50.695	3 digit pneumatic preset counter M5
50.700	3 digit pneumatic preset counter 4mm

ACCESSORIES	
1.405.404	Vestolit cover silver surround (IP65)
1.405.587	Vestolit cover black surround (IP65)
1.405.613	Protective cover with knob (IP55)
1.405.614	Protective cover with lock (IP55)

Kuhnke Predetermining Adding Pneumatic Counters show two lines of display. You set your target on the lower line using the mechanical push buttons. Pneumatic pulses are counted and displayed on the upper line. Starting from zero the upper line displays the total count until it reaches the target (pre-determined) value. A pneumatic output is then generated, which remains "on" until reset.

Model includes a manual push button to reset (lockable) and a port (Y) for reset by pneumatic pulse.

Alternative Products

Adding preset counter 5 digit 50.680 & 50.750

Subtracting preset counters 50.685 & 50.690

Disclaimer: The information shown in this document is for guidance only. No liability is accepted for any errors or omissions. The designer or user is solely responsible for the safe and proper application of the parts, assemblies or equipment supplied.

Downloaded from: www.kuhnke.co.uk / www.thetimerandcountercompany.com